

SPA 72

BEAUTIFY THE LOOK OF YOUR IN-GROUND SPA

Technical Specifications

SPA 72 LED Color Change Light

Input Voltage/Current

120VAC @ 85 ma

12VAC @ 1 amp

Power7.5 Watts

LED's72

Luminous Flux150 Lumen avg.

Light Length2.5 inch

Light Diameter2.6 inch

Power Connect. Medium Edison Base

Integral controller, Solid State, D/A Analog Color Drivers

Engineered for high brightness, reliability, and low cost power requirements, Life expectancy 100,000 Hours



The Spa 72 light from JEM Industries offers spa owners a quick, simple and cost effective method for adding color-changing lighting effects.

The Spa 72 is a replacement light featuring 72 ultra-bright, color-changing LEDs which produce millions of vibrant colors ideal for creating the perfect lighting atmosphere. The Spa 72 offers nine brilliant color operation choices plus synchronous operation in multi-light installations.

Ideal for existing spas or new installations, connection to the LED light is through a medium Edison base used in standard lighting fixtures which fit directly into a standard niche. Unlike fiber-optic installations, the Spa 72 doesn't require expensive retro-fits or controller boxes.

The Spa 72 is designed to be the last spa light you will ever need, with a life expectancy of 100,000 (11 years!) hours while operating on less than 10 watts of power.

OPERATION MODES :

1. White
2. Aqua
3. Purple
4. Blue
5. Yellow
6. Green
7. Red
8. Quick Cycle
9. Slow Cycle

Operation

- Quick Cycle mode is the fast, smooth, continuous color changing pattern through all colors.
- Slow Cycle mode is a slower (approximately 7 seconds) change between each color.
- To switch modes, turn the power switch off then on for 1/2 to 3 seconds to advance the mode to the next state.
- If the on/off switch is left in the "off" position for 4 to 8 seconds, the SPA 72's will resynchronize by flashing three times, at which point all of the lights in the system will be in the same state.
- If multiple SPA 72 lights are installed, the modes will synchronize together after the synch reset described above.
- The SPA 72 lights have a memory that when switched off for more than 8 seconds, all the lights will power up in the last state they were in when powered down. This allows user to leave lights in a favorite mode without having to hunt for it when re-powering up the lights.

Technology in Lighting

SALES OFFICE

2560 SUMMER BROOK ST
MELBOURNE, FL 32940

SALES OFFICE

2560 SUMMER BROOK ST
MELBOURNE, FL 32940

Phone: 321-768-7878

Fax: 321-768-8701

eMail: Sales@JEMIND.com

COLOR
MorphTM
.....
TECHNOLOGY

